smart door alarm V22
2G GSM Version

◇ Host specifications		Details
◇ **Chip platform**		RDA8955
◇ **Network Bands combination**		2G-GSM: B2\3\5\8;
◇ **Standby mode**		Single-card of Nano SIM
◇ **Receive diversity**		Supports
◇ **Data rate**		2G Data: EDGE
◇Positioning functions		**Description**
LBS	LBS position	Supports
	LBS accuracy	100-1000M (base on Amap database)
◇ Special features		**Description**
Ultra-low power consumption		Supports
Door open/close alarm		Supports
Phone calls		Supports
SMS text commands		Supports
In-built battery		Supports
Lithium battery charging circuit		Supports
Lithium battery charging protection		Supports
Remote voice monitoring		Supports
Charging boot		Supports
Audio		Supports with buzzer
button\type		Power on and off button/ SOS button

smart door alarm V22
2G GSM Version

◇Parameters	Description
Battery	2000mAh
Average standby current	4mA/h
Average working current	4mA/h
Working Temps	-20 ~ 70℃
Working Humidity	5% to 95% nonsolidifying
◇ Appearance	Description
◇ Product modeling	Door alarm device
◇ physical dimension	110*50*18mm
◇ Weight	108g
◇ Color options	White
◇ Packaging accessories	Description
◇ Host	*1
◇ Magnet	*1
◇ Plastic base	*1
◇ SIM card tray	*1
◇ Magnet USB cable	*1
◇ Screws and scres driver	*1
◇ User manual	*1

smart door alarm V22
2G GSM Version

◇App and software		Description
◇ UI Style		Squared Up
◇ Software functions	Real time tracking	check location, adjust location uploading intervals and navigate to the pet.
	Historical route	Check each single day's location in the latest 90 days.
	Geo-fence	1.GPS fence: Compare GPS locations and judge it gets in or out of the fence. 2.WIFI fence： Compare WIFI locations and judge it gets in or out of the fence.
	Settings	To set settings of the door alarm tracker. For example： 1.SOS number setting 2.Main monitor number is to get alarm SMS. 3.Door alarm setting 4.Vibration alarm setting 5.Noise sensor alart setting 6.horn alart remind 7.Alert model setting
	Alarm list	To display all alerts triggered by the tracker, including offline, low battery and fence in and out ones.
	Remind setting	Turn on all options to get alert notifications. Please turn on the smart phone's App permission for notifications.