4G GPS Tracking Pendant RF-V51

◇ Positioning Functions		Details
◇ **Chip platform**		ASR3603S
GPS	* GPS	Supports
	Chip module	Main chip internal integrated
	GPS signal	L1,1575.42MHz C/A code
	GPS channel number	22 channels
	GPS chip scale receiving sensitivity	Trace: -165dBm Capture: -148dBm
	GPS accuracy	5-15m
	GPS Antenna	Ceramic antenna
	* AGPS	Supports
	AGPS fast position time	Cold boot within 26 sec to locate
LBS	LBS position	Available
	LBS accuracy	100-1000M
WiFi	WiFi position	Supports
	WiFi chip module	Inbuilt
	WiFi Standard	802.11b \ 802.11g \ 802.11n
	WiFi accuracy	5-50M
◇Cellular Networks		Description
◇ **Support network frequency**		GSM \ WCDMA \ FDD-LTE \ FDD-TDD
◇ **Frequency bands**		**Model A:** 4G-FDD: Band 1/2/3/5/7/8/20 3G-WCDMA: Band 1/2/5/8 2G-GSM: Band 2/3/5/8
		Model B: 4G-FDD: Band 1/2/4/5/7/12/13/17 3G-WCDMA: Band 1/2/5 2G-GSM: Band 2/5
◇ **Standby mode**		Single Nano SIM Card
◇ **Receive diversity**		Supports

4G GPS Tracking Pendant RF-V51

◇ Special features	Description
Location check on the Internet	By Web Platfrom, IOS App, and Andorid App
Phone calls	SOS call, Speed dial, Whitelist incoming calls
Remote voice monitoring	Supports
SMS text commands	Supports
Blind spot supplement upload	Supports
Position drift processing	Supports
Historical route check	Supports
Built-in battery	Available
Ultra-low power consumption	Supports
Lithium battery charging circuit	Supports
Lithium battery charging protection	Supports
Charging boot	Supports
Audio	Supports
◇Parameters	Description
Battery	1000mAh
Average standby current	4mA/h
Average working current	8mA/h (upload position within every 10minutes)
Working Temps	-20 ~ 70℃
Working Humidity	5% to 95% nonsolidifying
Waterproof	IP67 Splash-resistant
◇ Appearance	Description
◇ Product shaping	Pendant style GPS tracking device
◇ Physical dimension	57.5*40*16.5mm (approx.)
◇ Net weight	45g (approx.)
◇ Color options	Black matte housing with orange buttons
◇ Buttons	3 keys: SOS key*1, Speed dial key*2
◇ Packaging accessories	Description
◇ Package type	Neutral Giftbox (base & lid style)
◇ Host device	1* V51 GPS pendant
◇ Lanyard	1* Pendant lanyard
◇ Charging cable	1* Magnet USB cable
◇ Screw driver & Screws	1* Screw driver; 2* Spare screws
◇ User guide	1* User manual

4G GPS Tracking Pendant RF-V51

◇App and software		Description
◇ UI Style		Squared Up
◇Software functions	Real time tracking	check location, adjust location uploading intervals, and one-click navigating to the wearer.
	Historical route	The latest 90 days' historical route of the wearer is stored on clound, accessible to check and playback.
	Geofence	Customizable GPS fence and WiFi fence, available to check the wearer's locations in realtime and get alterts when the wearer get in or out of the fences.
	Health	Calculate the wearer's activity amount, calorie consumption and exercise journey.
	Talk/Audio/Call	1. Two-way SOS voice call; 2. One-way voice monitoring: *Request the tracker to call the SOS number for voice monitoring;
	Settings	General setting panel of the GPS pendant, for example: 1. SOS number setting 2. Phone book number for whitelist incoming calls 3. Falld detection alert 4. Alarm Clock 5. Ringtone-to-Find the tracker 6. Refuse unfamiliar incoming call, etc.
	Alarm list	To display all alerts triggered by the tracker, including offline, low battery, and geofence in & out.
	Reminder setting	Turn on/off all options to get alert notifications. *Please turn on the smart phone's App permission for notifications.